

PORTABLE POWER PACK (P3)

The Portable Power Pack (P3) is the only mobile, multi-voltage Lithium-ion battery designed for moving industrial equipment. No more maintaining costly and heavy lead acid carts, as a single operator can unload or load an entire equipment fleet with the power and versatility of the Portable Power Pack. This tool is capable of moving industrial equipment with operating voltages of 24v, 36v or 48v. It is equipped with interchangeable brackets to allow for securing the P3 to a forklift carriage or LBR, as well as a tow handle and wheels for ease of mobility. The P3 charger consists of a 110VAC input with an output of 25 amps. The charger can be operated standalone or mounted.



BENEFITS



Maintenance
Free



Increase
Safety



Lower
Costs



Reduce Equipment
Downtime



Improve
Efficiency



Environmentally
Friendly

*Eliminates the need
for lead acid carts!*

APPLICATIONS

- Manufacturers
- Equipment dealers
- Equipment installations
- Rental/service companies
- Warehouse/distribution
- Large fleets

FEATURES

Telescoping handle

for suitcase style towing

Charging port

for use with P3 charger

Multi-voltage compatible

24v, 36v & 48v

State-of-Charge Indicator

for quick viewing

Side handles

for easy lifting

Interchangeable mounting brackets

for securing to forklift carriage or LBR

Steel case construction

for optimal durability

Wheels

for easy moving



OPTIONAL ADD-ONS

P3 Extension Cable Kit

- (1) 8' 4/0 SB175 - SB350 Red
- (1) 8' 4/0 SB175 - SB350 Grey
- (1) 8' 4/0 SB175 - SB350 Blue

SPECIFICATIONS

Portable Power Pack (P3)

Voltage(s)	24v, 36v, 48v
Capacity	63ah
Weight	94 lbs
Dimensions	15.75" x 7.6" x 32.9"
Output Connector Type	SB175 Red (24v), Grey (36v) & Blue (48v)
Max Continuous Discharge	63a Continuous
Max Peak Discharge (30 sec)	250a
Charge Time	2.5 Hours (0-100%)

P3 Charger

AC Input	110 VAC
DC Output	25a
Weight	30 lbs
Dimensions	14.25" x 5.75" x 23.75"
Charge Connector Type	Stacked Power Pole Connectors
Cooling System	Fans

*Disclaimer: The Portable Power Pack (P3) is not designed or intended to be used as a counterweight or load lifting for any and all models of forklifts / industrial equipment. The P3 is solely designed for forward or reverse travel and is not a direct replacement battery for any equipment. Please refer to the P3 Operating Manual or Warranty for further information.